

This application is submitted in the name of inventor John M. Pinneo, assignor to P1 Diamond, Inc., a California Corporation.

S P E C I F I C A T I O N

5

IMPROVED THERMAL MANAGEMENT COMPONENTS

RELATED APPLICATIONS

Sub P1 This application claims priority from prior pending Provisional Application serial No. 60/162,429, filed October 28, 1999.

10

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to the use of economically feasible diamond materials thermal management of heat-generating systems. More particularly, the present invention relates to the use of economically feasible diamond materials for thermal management of heat-generating systems including active electronic devices such as integrated circuits.

2. The Prior Art

Active electronic devices such as transistors, laser diodes, vacuum tubes, and other electron control components generate waste heat as a common and necessary result of their operation. For purposes of this application, active electronic device is meant to encompass any device that consumes electrical energy and transforms a portion of that energy to heat.

Depending on the specifics of the device, said specifics including its geometry, power dissipation, duty cycle, material, and operational requirements, the waste heat generated may constrain the device performance in an unacceptable manner or to an unacceptable degree. For example, in laser diodes, the extreme power density necessary to excite laser emission from the narrow, shallow lasing region causes heating in the device which presents particularly difficult thermal management problems. As laser diode brightness requirements increase, so too do the requirements for rejection of waste heat.

10 A further example may be found in microprocessors. Microprocessors are understood by those skilled in the art to comprise integrated circuits composed of multiple transistors which control the flow of electrons so as to effect computation in a useful fashion. At this writing, microprocessors are primarily fabricated using silicon both as the electronically active elements (transistors) and as the

15 mechanical support material for those elements. This is commonly done by fabricating transistors on the surface of a silicon wafer, the transistor structures being thin compared with the bulk of the wafer thickness underlying the active device layers. It will be appreciated that although reference is made in this discussion to silicon integrated circuits such as microprocessors, this is not

20 intended by way of limitation with regard to the material used to fabricate such devices, and other materials such as germanium, gallium arsenide, gallium aluminum arsenide, and gallium nitride are included without limitation.

Microprocessors, like other electronic devices, generate heat as a consequence of operation. Owing to the physics underlying its construction, a microprocessor generates more heat the more rapidly it is made to operate. Thus, as microprocessors are made to provide higher clock rates (an index of the speed with which the transistors in the processor are made to switch on and off, which is the basis for their computational functions), they generate greater heat which must be disposed of to maintain the microprocessor temperature within its safe operating limits.

Microprocessors present particularly difficult thermal management problems. They are composed of millions of transistors and their heat generation rates depend on their clock speeds and the particular software codes they execute, among other parameters. In addition, their temperature or thermal profiles are often nonuniform. That is, certain areas of the processor will be hotter than others, and these hot spots will limit the overall performance of the device, even though other regions are operating well within their thermal limits and could be operated faster but for the hot spot regions.

In common practice, microprocessors are mechanically constrained by a package, which consists of components that support and position the processor in space, provide electrical connections, allow for the transference of waste heat

away from the device, and provide the requisite degree of mechanical integrity and isolation from environmental degradation. It will be appreciated by those skilled in the art that these requirements are often in opposition and pose difficult engineering tradeoffs to the package designer. Once a processor has been

5 packaged, it is often affixed to a circuit board whereby it interfaces with other integrated circuits such as memory, buss management chips, or other integrated circuits that co-operate with the processor in its operation.

There are many ways to package microprocessors. For processors that have

10 significant thermal rejection requirements, a critical element of their packaging is the component through which heat from the processor first passes on its way to the ultimate heat-dissipation modality in the system. This component, being the first element in the chain of transport of waste heat away from the processor, greatly affects the efficiency of heat transport, and is subject to a variety of conflicting

15 requirements that, taken together, strongly constrain the choice of materials that can be used to fabricate the component. The component is often called a heat spreader, and is usually bonded to the processor by means of thermally conductive adhesive, or solder, or by use of mechanical compression or other means of affixing it in intimate contact to the processor. It should be noted that the

20 designation "heat spreader" is a convenience for discussion of the package component and not a limiting designation.

Referring now to FIG. 1, a schematic representation shows a common configuration of a microprocessor, heat spreader, and overall package. The figure shows a "BGA (Ball Grid Array) package", a configuration in which a microprocessor is mounted on an array of small solder spheres that primarily provide electrical contact to the microprocessor. They also lend a degree of mechanical support and thermal conduction, although the latter is relatively low because the thermal conductivity of solder alloys is poor and the total surface area available for thermal conduction is small compared to the area of the microprocessor.

10

The principal thermal pathway in this configuration is out the back of the microprocessor, through the heat spreader, through the package lid, and into the heat sink, from which heat is extracted, often by a moving fluid, for dispersal to the environment. Although this figure represents one particular configuration of microprocessor package, it is representative of most others in depicting the need for a high thermal conductivity pathway through which to reject heat produced during operation.

15

The package component, or heat spreader, immediately adjacent to the microprocessor must exhibit high thermal conductivity to facilitate the transport of heat away from the processor. It must also possess a thermal expansion coefficient that is sufficiently similar to that of the processor material to avoid

20

exerting destructive forces on the processor which arise out of the differential thermal expansion of the processor and heat spreader. It must also be capable of supporting an intimate bond with the processor through adhesive, solder, or other means. If needed, it must provide electrical isolation without detriment to thermal transfer. These requirements are mutually conflicting, and have not heretofore been susceptible of a particularly favorable solution.

Materials to date used for microprocessor heat spreaders have been selected from metals and metal alloys such as copper/tungsten or copper/molybdenum. ✓
Certain ceramic materials, such as beryllium oxide or aluminum nitride have also been used as heat spreaders for electronic devices. These materials are characterized by having thermal conductivities in the range of approximately 1 to approximately 3 watts/centimeter/degree Centigrade (hereafter W/cm/°C). For reference, pure copper has a thermal conductivity of approximately 4 W/cm/°C.

15

It will be immediately appreciated by those skilled in the art that the materials in common use for heat spreaders in microprocessor packaging exhibit lower thermal conductivity by far than a commonly available metal, copper, which would otherwise be a better choice of material for the requirement. Copper, however, has a thermal expansion coefficient much greater than that of silicon, and cannot be used in direct proximity with a silicon device due to the high probability of fracture of the silicon as a result of differential thermal expansion

during operation. For comparison, silicon has a thermal expansion coefficient of approximately 4.1 parts per million per degree Centigrade, while copper, copper/tungsten alloy, beryllium oxide, and aluminum nitride are respectively approximately 17, 5.6-7, 8, and 4.5, in the same units. Aluminum nitride provides
5 a good thermal expansion match to silicon, but its thermal conductivity is only about 1.7 W/cm/°C. Most designers therefore select copper/tungsten alloys because they are less costly than aluminum nitride and provide similar thermal conductivity.

10 The problem of thermal expansion becomes more severe as the size of the microprocessor or other electronic device increases. Because differential expansion forces arise over the entire extent of the interface between heat spreader and microprocessor, the larger the interface, the greater the total force exerted on the processor, and the higher the probability of fracture of the processor material.
15 For purposes of this disclosure, we intend to cover electronic devices, including microprocessors, having a surface area in contact with the heat spreader or other first package element of one square centimeter or greater.

As a result of differential expansion forces, package designers have been
20 forced to employ materials of inferior thermal conductivity as heat spreaders in device packages. This in turn has limited the ability to transport waste heat away

from microprocessors, constraining their performance to a substantial and unacceptable degree.

It has long been known that diamond is an ideal potential-candidate for heat
5 transfer applications such as described above. Diamond, both natural and
synthetic, is known in the art to exhibit thermal conductivity superior to all other
known materials. Diamond manufactured by chemical vapor deposition, a modern
and widely studied means of diamond synthesis, has been shown to exhibit
thermal conductivity in excess of 20 W/cm/°C. At the same time, diamond's
10 thermal expansion coefficient is approximately 1 to $1.7 \times 10^{-6}/^{\circ}\text{C}$ over the
operating temperature range of silicon-based microprocessors. Finally, diamond
has the highest Young's modulus, or stiffness, of any known material, excluding
unidirectional moduli of certain fibers not applicable to the present invention.
The combination of these properties is unique to diamond.

15

It has not been previously possible, however, to provide diamond material
for use in such applications at a price that permits their commercial use.
Integrated circuits such as microprocessors are fabricated on integrated circuit dice
having areas of 1 square centimeter or larger. Use of diamond material for heat
20 transfer from such devices having areas as large as 1 square centimeter or larger
has been, at best, a laboratory curiosity because of the prohibitively high expense
of providing the diamond material.

Diamond synthesis through chemical vapor deposition (CVD) is by now a well-established art. Commercial diamond deposition systems are available and products employing CVD diamond are routinely sold for commercial applications ranging from cutting tools to heat spreaders.

All diamond CVD processes to date have been characterized by very low process efficiency in terms of the amount of diamond produced in response to consumption of energy and synthesis materials. There has been a long-felt need within the CVD diamond industry to improve diamond CVD process efficiencies. This long felt need has given rise to vigorous prior but unsuccessful efforts to achieve significantly higher process efficiencies.

Diamond chemical vapor deposition is accomplished by energizing an appropriate gas mixture (most commonly containing a preponderance of hydrogen and a minor hydrocarbon constituent, the latter being the source of carbon which is deposited as diamond) in a suitable deposition reactor and providing means for the diamond precursor chemical specie(s) generated by said application of energy to encounter a surface whose temperature, chemistry, and surface preparation properties permit the nucleation and growth of diamond layers in a manner well-known to those skilled in the art.

It is thought, and there is considerable supporting and little contradicting evidence, that a key step in the formation of diamond through the majority of useful diamond CVD processes is the dissociation of ordinary molecular hydrogen gas to form atomic hydrogen. Once formed, this species effects several actions known to be required for diamond CVD to occur at useful rates: it stabilizes carbon in the sp^3 (diamond) bonding configuration and forestalls the formation of undesirable sp^2 (graphitic) bonds; it abstracts hydrogen from hydrocarbon precursor species and thereby makes carbon available for incorporation in the growing diamond lattice; and it selectively reacts with, and returns to the gas phase, those small graphitic domains which may from time to time appear during the diamond CVD process, thereby preventing the formation of graphite-contaminated diamond which would be of no significant utility.

While the details of surface chemistry underlying diamond CVD remain to some degree obscure, it is widely observed that the successful synthesis of diamond through most CVD methods requires production of atomic hydrogen. The economics of diamond CVD processes are essentially the economics of generating atomic hydrogen.

A few instances of diamond CVD requiring little or no atomic hydrogen are known to the art. A laser-driven diamond CVD process developed by QQC, Inc., appears not to require hydrogen in its precursor atmosphere. Similarly, diamond

CVD using microwave-assisted plasmas has been accomplished under conditions of reduced hydrogen concentration. While these results suggest subtleties to diamond CVD chemistry that remain to be elucidated, they confirm the fundamental scheme in which a gas, or mixture of gases, is energized by a variety of modalities to effect diamond CVD under appropriate conditions as specifically required by the circumstances chosen by the practitioner of the art. To date, none of the low-hydrogen diamond CVD processes has demonstrated commercial utility.

10 In all known diamond CVD processes having commercial utility, production of atomic hydrogen is required and is the primary energy-consuming step in those processes. The costs of producing atomic hydrogen in large quantities are considerable, and include the direct cost of energy as well as the cost of equipment needed to apply that energy in a useful manner. As will be seen, the diamond CVD processes that constitute the current art are extremely inefficient, leading to very high energy and equipment costs.

The heart of diamond CVD process inefficiency lies in the short lifetime of the atomic hydrogen species and in the energy cost of creating that species.

20 Atomic hydrogen is thermodynamically driven to recombine to form molecular hydrogen, which plays no significant role in diamond CVD. The recombination, or loss, of atomic hydrogen proceeds very rapidly on surfaces and comparatively

slowly in the gas phase. This relationship arises because recombination of two hydrogen atoms requires a release of energy in order to proceed. In the gas phase, quantum mechanical effects prohibit the release of the recombination energy when only two hydrogen atoms collide. Thus, gas-phase recombination of atomic

5 hydrogen requires simultaneous collision of at least three bodies, two of which are hydrogen atoms. The third body, which may be another hydrogen atom, molecule, or non-hydrogen molecule, dissipates the recombination energy as kinetic energy.

On surfaces, the required kinetic energy dissipation pathway is provided by
10 the surface itself. The recombination of atomic hydrogen on surfaces is a two-body collision because of this, and it proceeds very rapidly compared to gas phase recombination. The recombination energy appears as heat in the substrate. Much of the substrate heating observed in diamond deposition arises from the energy of atomic hydrogen recombination.

15

Because the manufacture of atomic hydrogen requires substantial energy, and because the species, once made, is continuously and rapidly destroyed by recombination with itself and with other molecular species, successful diamond CVD requires manufacture of enormous amounts of atomic hydrogen compared
20 with the amounts which actually participate in diamond deposition. This is the root of the inefficiency of current diamond CVD art.

A common feature of nearly all diamond CVD processes is the manufacture of atomic hydrogen at distances relatively remote from the deposition region.

Thus, microwave diamond CVD entails the formation of microwave plasma regions, the main bulk of which do not contact the deposition surface and which
5 may be several inches away from that surface. This provides ample opportunity for loss of valuable atomic hydrogen through recombination.

Similarly, diamond CVD practiced with heated filaments suffers from relative inefficiency of atomic hydrogen production (due to limits on filament
10 temperature) as well as losses due to the inability to locate filaments in immediate proximity to the deposition surface, which limitation arises from substrate overheating due to radiation of energy from the filament.

A third common means of diamond CVD, use of electrically-driven plasma
15 torches which manufacture atomic hydrogen principally through superheating a stream of molecular hydrogen, must transport manufactured atomic hydrogen in a supersonic stream from the energy application point to the deposition region, which is typically at least several inches away. Much atomic hydrogen is lost, but because the supersonic gas stream impacts the substrate at high velocity,
20 stagnation boundary layers are thin, and the diffusive flux of atomic hydrogen to the surface is relatively large, giving high growth rates for this method. Overall efficiency, however, remains poor, because of the enormous overproduction of

atomic hydrogen inherent in the process compared with the small fraction that reaches the growth surface.

Diamond CVD growth efficiency is often expressed in terms of the weight of diamond formed per unit time as a function of the amount of power supplied to the system. While this figure of merit ignores the consumption of precursor gases, it is a useful index of the energy efficiency of a diamond CVD process and makes possible an efficiency comparison among different diamond CVD processes. A more comprehensive index of diamond growth efficiency will be presented below.

As reported (MRS Bulletin, September 1998, volume 23, no. 9, pp 22-27, in particular figure 3 on page 24), the best diamond CVD processes have reached a power efficiency of approximately 6.25 kilowatts (kW) per hour per carat of diamond deposited. A carat is equal to 0.2 grams. As reported in this reference, this efficiency level has been reached by application of successively greater amounts of power to the growth system, reaching up to 200kW in some systems.

Unfortunately, the capital cost of equipment capable of sustaining such extremely energetic processes is large. Thus, the modest increase in deposition efficiency gained by use of more power is offset by the resultant economic penalty. The net result of this technology development pathway has been an increase in diamond deposition rate without significant decrease in deposition

cost. Breakout from the constrained high cost of diamond synthesis has been a long-sought goal in the art.

A more useful diamond CVD growth efficiency index should account for
5 consumption of gases as well as energy use. In the same manner that energy
consumption can be expressed in terms of kilowatt-hours per carat of diamond
produced, hydrogen and methane consumption can be expressed in terms of
standard liters per carat of diamond produced. If gas consumption in standard
liters of hydrogen and methane per carat of diamond produced is added to
10 electrical power consumption in kilowatt-hours per carat of diamond produced,
and the inverse of that sum is computed, an index results that correctly reflects
diamond CVD process efficiency by varying inversely with energy and gas
consumption rates. This index, referred to herein as the "raw composite growth
efficiency" makes it possible to compare the growth efficiencies of disparate
15 diamond CVD processes.

Process efficiencies for the principal means of diamond CVD are shown in
Table 1. The data have been compiled from literature reports and from experience
with each of the listed modalities. Energy efficiency is expressed in terms of kW-
20 Hr/carat of diamond produced, while raw material consumption is expressed as
liters of gas consumed per carat of diamond produced. Raw composite growth and

normalized composite growth efficiencies are calculated as stated above, and are presented with the efficiency of the arc jet modality normalized to 100%.

	Arc Jet	Hot Filament	Microwave	Current Invention
Power consumption, KW-Hr/carat	6.8	44.6	34.1	2.1
Hydrogen consumption, standard liters/carat	2,048	669	546	86
Methane consumption, standard liters/carat	102.4	33.4	27.3	4.3
Raw composite growth efficiency	0.000464	0.00134	0.00165	0.00792
Normalized composite growth Efficiency	100%	289%	355%	1,700%

Table 1 – Comparative Diamond CVD Process Efficiencies

The foregoing table discloses the relative growth efficiencies of diamond CVD methods, including that achieved by this invention. No diamond deposition method, other than this invention, is known to produce diamond at a raw composite growth efficiency greater than approximately 0.00165 as computed according to the method shown above. These growth efficiencies are understood to be in reference to CVD diamond material of commercially useful purity. One means of establishing purity of a CVD diamond material, and a means commonly

employed in the art, is through use of Raman spectroscopy. So measured, the Raman signature of commercially useful CVD diamond shows an sp^3 (diamond-bonded carbon) peak having a full width at half maximum value of 12 wavenumbers or less, and exhibits non- sp^3 features of intensity less than 50% of the sp^3 peak intensity in the wavenumber region from 1200 cm^{-1} to 1700 cm^{-1} .

BRIEF DESCRIPTION OF THE INVENTION

The present invention provides a superior solution for transport of waste heat away from microprocessors or other electronic devices without generating destructive interface forces. The present invention employs high-efficiency diamond as the material for the heat spreader in intimate contact with the microprocessor or other heat generating electronic device.

The diamond employed in the present invention is deposited using a process having greatly enhanced growth efficiency and is thus cost effective to employ for the purposes set forth herein. Diamond materials employed in the present invention are referred to herein as "high-efficiency" diamond materials. That term, as used herein, shall be used to identify diamond material having a composite growth efficiency greater than about 0.003.

20

According to one embodiment of a method according to the present invention, atomic hydrogen and other requisite diamond deposition species are

generated in intimate proximity to the deposition surface, thereby greatly reducing the amount of atomic hydrogen and other precursors lost to the process, and concurrently greatly reducing the amount of energy and precursor material required to achieve a given diamond deposition rate.

5

According to another embodiment of a method according to the present invention, atomic hydrogen and other requisite diamond deposition species are generated at pressures greater than 20 Torr using plasmas excited at powered electrodes from energies at frequencies greater than 50 MHz.

10

Methods for cooling heat-generating devices, such as electronic devices and, in particular, semiconductor devices, according to the present invention comprise growing high-efficiency diamond material and thermally coupling the high-efficiency diamond material to the heat-generating devices. The high-efficiency diamond material may also be thermally coupled to heat spreaders or sinks for dissipation of the heat conducted away from the heat-generating devices.

15

BRIEF DESCRIPTION OF THE DRAWING FIGURES

FIG. 1 is a schematic representation showing a common configuration of a heat-generating device in the form of a microprocessor, heat spreader, and overall package.

20

FIG. 2 is a schematic representation of a first exemplary process according to the present invention for synthesizing high-efficiency diamond material.

FIG. 3 is a schematic representation of a second exemplary process
5 according to the present invention for synthesizing high-efficiency diamond material.

FIG. 4 is a schematic representation showing a heat-generating device in the form of a microprocessor, a heat spreader, and overall package configured
10 according to a first embodiment of the present invention.

FIG. 5 is a schematic representation showing a heat-generating device in the form of a microprocessor, a heat spreader, and overall package configured according to a second embodiment of the present invention.
15

DETAILED DESCRIPTION OF THE INVENTION

Those of ordinary skill in the art will realize that the following description of the present invention is illustrative only and not in any way limiting. Other embodiments of the invention will readily suggest themselves to such skilled
20 persons.

The present invention comprises the use of a high-efficiency diamond material as a component interposed between a heat source and heat sink as part of a thermal transport or thermal management system. This invention makes particular reference to use of diamond materials with integrated circuits, including
5 microprocessors, and other elements of their supporting packages.

Referring now to FIG. 2, a schematic representation illustrates a first actual exemplary process according to the present invention for synthesizing high-efficiency diamond material for use in the present invention.

10

Specifically, the process illustrated in FIG. 2 employs a chamber 10 affording a controlled atmosphere and pressure, wherein is disposed a substrate support 12 for supporting a substrate 14 on which it is desired to deposit diamond. A heat source 16 and temperature measurement and control system 18 are
15 employed whereby the temperature of the deposition substrate may be controlled within a range known to those skilled in the art to support diamond growth. A signal source 20 generates energy in the form of alternating current having a frequency greater than approximately 50 MHz may be applied to the substrate support structure in such a way as to cause a high electric field to appear at the
20 deposition substrate surface in order to cause the electrical breakdown of gases immediately adjacent to that surface with the formation of a plasma near the deposition substrate surface.

More specifically, an actual embodiment of this invention employs a metallic rod 22 suitable for the conduction of electrical energy at 400 MHz. The rod is fixed at its base through an electrically nonconductive support 24 that provides mechanical stability and allows the structure to be energized with 400 MHz energy. The rod is approximately 6 inches in overall length and is oriented substantially vertically, although this orientation is not critical to the operation of methods according to the present invention. At the unfixed end of the rod, a disc having a diameter of approximately 1 inch and a thickness of approximately 1/8" is attached to the rod to form substrate support 12 at the end of the rod suitable for the support of a silicon wafer or other suitable substrate on which it is desired to grow a diamond coating. This disc and rod are fabricated from materials compatible with the environment required for diamond deposition as is known in the art. Molybdenum is a suitable material among others known in the art.

15

As shown in FIG. 2, energy at 400 MHz is admitted into the deposition chamber and applied to the base of the above-described rod/support structure such that the rod 22 and support 12 form an electrical quarter-wave component well-known to those skilled in the art and designated herein as the powered electrode. A characteristic of such a structure when energized in the manner described is the appearance of high electrical fields at the end of the structure distant from the end at which the energy is applied. In this case, the electric field is highest at the disc

20

which supports the deposition substrate. This provides the energy needed to achieve electrical breakdown of the gases contained within the growth chamber and cause the formation of a plasma adjacent to the deposition substrate surface, as will be detailed further below. The 400 MHz electrical energy may be provided

5 by radio-frequency generator 20 that embodies controllable power output, a coaxial cable for transmitting energy from the generator, an electrical impedance matching device to accomplish efficient coupling of energy from the generator to the powered electrode structure, and equipment for monitoring the amounts of incident and reflected energy in the system, not shown but well known to persons

10 of ordinary skill in the art.

A counter electrode, 26 formed from a molybdenum screen in the shape of a disc having a diameter of about one inch, consisting of molybdenum wire having a wire gauge of approximately 16 and a wire/inch weave of approximately 16, is

15 supported parallel to, and spaced approximately 0.5 inch away from, the exposed face of the substrate support disc. This counter electrode 26 is connected to electrical ground (shown as the chamber wall in FIG. 2) and assists in the concentration of electric fields at the deposition substrate 14, thereby facilitating the breakdown of gas and formation of plasma in the desired region. While the

20 counter electrode 26 is a convenient adjunct to the invention, reducing the criticality of the dimensions of the powered electrode, the present invention is operative without such an electrode.

Quartz-halogen radiant heating lamp 16 of a type well-known in the art, commonly used and herein employed to adjust the temperature of the deposition substrate to the desired value prior to plasma ignition is placed behind the

5 molybdenum screen counterelectrode 26. Radiant energy proceeds from the quartz heating lamp through the molybdenum screen counter electrode 26 and impinges on the deposition substrate 14, causing its temperature to increase. The deposition substrate temperature is monitored, and the quartz heating lamp is controlled so as to achieve and maintain the desired temperature at the deposition

10 substrate 14. It will be apparent to those skilled in the art that this controlled heating system may be altered or replaced by any of a number of other well-known means for achieving substrate temperature control, including resistive radiant heating, resistive direct heating, induction heating, and control of substrate heating by control of the power applied to achieve plasma formation.

15

A silicon wafer common in the industry having a diameter of about 1 inch and a thickness of about .5mm which has been prepared for diamond deposition by nucleation enhancement means well-known to the art (in this case, minor abrasion with 1 micron diamond abrasive) is employed as substrate 14 and is placed on the

20 powered electrode facing the counter electrode. The deposition chamber 10 is closed, and gases are evacuated from the chamber by means of a vacuum pump included in chamber exhaust and pressure control 28. When a pressure of .01 Torr

or less has been achieved, gases suitable for diamond deposition are admitted to the chamber until the pressure is about 5 Torr, at which pressure the atmosphere is maintained by means of a pressure transducer, a pressure controller, and a controlled valve in the chamber gas exhaust line included (but not shown) in

5 chamber exhaust and pressure control 28, all configured in a manner well understood by persons of ordinary skill in the art. A suitable gas mixture and flow rate has been found to be 200 standard cubic centimeters per minute (sccm) of hydrogen and 10 sccm of methane from gas supply 30, each gas having a purity level of not less than 99.999%. Other gas compositions known to the art of

10 diamond CVD are operable, and this particular mixture is specified as illustrative and operable without limitation thereto.

The quartz heating lamp 16 is energized to bring the deposition substrate 14 (the silicon wafer) to the desired temperature, in this case about 750 degrees

15 Centigrade. This temperature is within the broad range of temperatures known to support diamond CVD and is specified without exclusion of other suitable temperatures known in the diamond deposition art. 400 MHz energy is then applied to the powered electrode to cause the ignition of a plasma between the powered electrode and the counter electrode. It has been commonly observed that

20 plasma ignition occurs when at least 50 watts of energy is applied. When plasma ignition has been achieved, the chamber pressure control system is manipulated to cause a slow (typically 10 torr/minute) increase in pressure to the deposition

pressure of 100 Torr. During this pressure increase, the 400 MHz energy source is controlled to increase the amount of applied energy to sustain the plasma between the powered electrode and the counter electrode. As the pressure is increased, 400 MHz energy is delivered in increasing amounts and contributes to substrate heating. Accordingly, the quartz heating lamp 16 is automatically controlled to maintain substrate temperature at approximately 750 degrees Centigrade. While the particular power required to sustain the plasma will vary with the details of each individual apparatus, it has been observed that about 200 watts of 400 MHz energy is adequate to sustain a plasma as described at a pressure of about 100 Torr.

As the chamber gas pressure increases from 5 Torr to 100 Torr and additional 400 MHz energy is applied, it is observed that the plasma maintains its diameter of approximately 1 inch but shrinks from the space between the two electrodes to form thin plasma regions or "skins" on each of the powered electrode and the counter electrode. Measurements have shown that at 100 Torr, the plasma on the powered electrode has a thickness of approximately 2 mm, and is so intimately adjacent to the deposition substrate surface that it is difficult to determine the distance between the surface and the plasma, the distance being less than 1 mm. This relationship is completely novel in the art of diamond CVD and underlies the efficacy of this invention.

After maintaining deposition at 200 watts of applied energy for 3 hours, all energy inputs to the process are shut off and the apparatus is allowed to cool to room temperature. The chamber 10 is evacuated and filled with air. The chamber 10 is opened and a diamond layer is found to have grown on the deposition

5 substrate 14 to a thickness of approximately 84 microns. This represents a deposition power efficiency of approximately 0.8 KwHr/carat, approximately 7.8 times (780%) as efficient as the known state-of-the-art maximum of 6.26 KwHr/carat. The raw composite growth efficiency is 0.00792. Diamond growth is also noted on the counterelectrode 26, the thickness being less than that noted
10 on the powered electrode. Diamond growth on the counterelectrode 26 has been omitted from the efficiency calculation, rendering that calculation conservative. The present invention contemplates reactors designed so as to make use of the diamond material grown on counterelectrode structures to provide enhanced utility.

15

Another actual exemplary process according to the present invention is shown with reference to FIG. 3. Because the apparatus for performing the process described with reference to FIG. 3 is similar in nature to the apparatus shown in FIG. 2, elements in FIG. 3 which correspond to elements in FIG. 2 will be
20 designated by the same reference numerals used in FIG. 2.

Accordingly, a suitable metallic deposition chamber 10 is provided having a chamber exhaust and pressure control system 28 for control of atmospheric pressure and composition. As in the embodiment discussed previously, the rod 22 and substrate support 12 are provided for supporting and energizing a deposition substrate 14. The temperature of the deposition substrate 14 may be measured and controlled as in the previous embodiment by temperature measurement and control system 18. Energy of a frequency of approximately 150 MHz is applied from a generator source to the structure holding the substrate and thereby to the substrate itself. Substrate 14, comprising a silicon wafer 8 inches in diameter treated for diamond nucleation by means well-known in the art, is placed on the rod 22 and support 12 or other structure suitable for holding such a wafer and fabricated from a material compatible with the requirements of diamond chemical vapor deposition. One such material is molybdenum, with others being tungsten, silicon carbide, silicon nitride, or others known to the art. A counterelectrode 26 having a disc geometry with a diameter of approximately 8.50 inches is disposed in opposition to the substrate 14, and is separated from the substrate surface by approximately 0.25".

The deposition chamber 10 is evacuated to a base pressure of less than 0.01 Torr and process gases consisting of hydrogen and methane are admitted to the deposition chamber from gas supply 30 at a mixture ratio of 95% hydrogen, 5% methane, and the chamber pressure is regulated at 5 Torr. When 5 Torr pressure is

reached, the 150 MHz source is energized and a plasma is observed to cover both the deposition substrate 14 and the counterelectrode 26, and to fill the space in between these two structures.

5 Chamber pressure is slowly increased to 150 Torr, with concurrent increase in the power level of the 150 MHz source, and with concurrent adjustments of the impedance matching device (not shown) to maintain a good electrical match between the power source 20 and the deposition system. As pressure increases, the plasma is observed to fade from the interelectrode space and to persist as a thin
10 structure on the deposition substrate 14 and on the immediately opposed surface of counterelectrode 26. At a pressure of 150 Torr, approximately 75kW of 150 MHz energy is required to maintain a uniform plasma over the deposition substrate 14.

 After a duration of seven hours, the deposition system is shut off, and
15 allowed to cool. A diamond film is observed to have grown over the silicon deposition substrate to a thickness of approximately 120 microns. The power deposition efficiency is calculated to be 1.4 kWhr/carat of diamond deposited. The raw composite growth efficiency is 0.00832. The normalized composite growth efficiency is calculated to be approximately 17.6 times, or 1780%, of the
20 efficiency of the 100% reference growth efficiency of the arc jet method.

Presentation of the foregoing illustrative embodiments is not by way of restriction to those methods. For example, numerous extensions are contemplated of those embodiments in which energy is provided through application of one or a combination of two or more other sources such as lasers or other illumination
5 sources, electromagnetic radiation outside the visible spectrum, radiation from nuclear sources, pressure or shock waves, thermal energy, energy from chemical reactions, etc. Processes in which reactants are supplied to the atmosphere to which energy is supplied by through phase change(s) from liquid to vapor, or from solid to vapor, or by finely subdividing reactants in the solid or liquid form in
10 order to disperse them in the growth atmosphere are also contemplated according to the present invention.

Following synthesis of raw diamond material, manufacturing finished diamond materials may be achieved through use of techniques such as laser
15 cutting to achieve the requisite shape and dimensions, mechanical grinding and polishing to produce the required thickness, flatness, parallelism, and surface finish, and sputtering and/or physical vapor deposition to deposit those metal coatings that may be needed to support solder or braze attachment between the diamond and other components. These techniques are all well known to those
20 skilled in the art, and are available from a wide range of commercial suppliers of equipment for fabricating ceramic materials.

According to the present invention, a high-efficiency diamond material having a surface area equal to at least the area of the heat source may be employed. Diamond materials having a surface area greater than that of the heat source are specifically contemplated in this invention and provide an additional
5 facilitation of heat transfer due to their greater area.

As illustrated in FIG. 4, a heat source 40 in the form of a microprocessor die and a high-efficiency diamond material 42 according to the present invention may be constructed by providing a thermal interface 44 using standard soldering,
10 brazing, and/or adhesive bonding that provide a sound mechanical and thermal bond between the heat source and the diamond. These effect a good thermal transfer interface, and bond the heat source and high-efficiency diamond material mechanically with a bond strength dependent on the particular attachment technology employed. Thus, microprocessor die 40 employs ball grid array 46 to
15 make electrical connections to package bottom 48. A first surface of high-efficiency diamond material 42 is mechanically bonded to microprocessor die 40 and a second surface of high-efficiency diamond material 42 is mechanically bonded to package lid 50. Also shown in FIG. 4 is heat sink 52 thermally coupled to package lid 50. Persons of ordinary skill in the art will readily appreciate that
20 the illustration of FIG. 4 is exemplary only and is not intended to be limited to the particular packaging scheme there shown.

The bonded mechanical interface illustrated in FIG. 4 gives rise to generation of shear forces at the interface if the heat source has a different coefficient of thermal expansion than that of diamond. The sign and magnitude of this interface force will depend on the difference in thermal expansion coefficient values, and on the degree of heating or cooling above or below the temperature at which the bond was made.

As shown by example in FIG. 5, a similarly useful thermal interface may be achieved without mechanical bonding through interposition of a thin, low-friction, thermally-conductive compliant material between the heat source (microprocessor die 40) and the high-efficiency diamond material 42. In FIG. 5, microprocessor die 40 employs ball grid array 46 to make electrical connections to package bottom 46. A first layer 54 of a thin, low-friction, thermally-conductive compliant material is disposed between first surface of high-efficiency diamond material 42 and microprocessor die 40.

The thin, low-friction, thermally-conductive compliant material layer 54 may comprise, for example, thin sheets of flexible graphite (available commercially under the trade name Grafoil). This layer 54 is interposed and compressed into intimate contact with the heat source 40 and the high-efficiency diamond material 42 through use of common spring clip 56 (two shown) or other mechanical mounting scheme that provides a suitable level of compressive force.

Persons of ordinary skill in the art will appreciate that a second layer 58 of the thin, low friction, thermally conductive compliant material may also be employed between the high-efficiency diamond material 42 and the package lid 50 in other embodiments of the present invention as also shown in FIG. 5. Also shown in FIG. 4 is heat sink 52 thermally coupled to package lid 50. As with FIG. 4, persons of ordinary skill in the art will also readily appreciate that the illustration of FIG. 5 is exemplary only and is not intended to be limited to the particular packaging scheme there shown.

10 The advantage of the embodiment of FIG. 5 for effecting a thermal interface is that it provides a means for transmitting heat without also transmitting significant mechanical shear force. Therefore, a heat source with a thermal expansion coefficient different from that of diamond can be employed without generation of large mismatch forces at the interface. This is an important
15 advantage for using diamond materials in packaging electronic devices made from silicon, gallium arsenide, and/or other device materials that possess expansion coefficients different from diamond and that are fragile and susceptible to breakage through interface shear force.

20 The thickness of the high-efficiency diamond material will necessarily vary in accord with the specific geometry of the heat source to which it is affixed. In this embodiment, the high-efficiency diamond material thickness lies between 100

microns and 2000 microns, preferably between 300 microns and 800 microns. As is readily understood by persons of ordinary skill in the art, the particular thickness to be most advantageously employed may be determined through modeling of the thermal characteristics of the heat source, the high-efficiency diamond material,

5 and the remainder of the heat transport system.

Several advantageous aspects of the present invention will be readily apprehended by those skilled in the art. First, the use of diamond, with its superior thermal conductivity, enhances the transfer of heat from the heat source to a

10 degree not achievable through use of non-diamond materials. Second, the close matching of the thermal expansion coefficients of diamond and silicon minimizes the forces generated at the interface between the microprocessor heat source and the high-efficiency diamond material. Third, diamond's extreme stiffness resists deformation, and the high-efficiency diamond material thereby mechanically

15 isolates the heat source from interface stresses generated at the side of the high-efficiency diamond material distant from the heat source. This in turn means that common materials with good thermal conductivity, such as copper or aluminum, may be attached to one side of the high-efficiency diamond material as part of the heat rejection system without concern for stress-induced failure of the

20 microprocessor attached to the other side of the diamond. This increases the efficiency of heat transport in the system.

In an exemplary embodiment of the present invention, a high-efficiency diamond material measuring 1" x 1" x 0.3mm thick is employed, with its major opposed surfaces having been prepared with a series of metals, said metals being applied by sputtering in the sequence and thicknesses of: titanium, 200

5 Angstroms, platinum, 1000 Angstroms, gold, 10,000 Angstroms, the titanium layer being immediately adjacent to the diamond surface on each major side of the high-efficiency diamond material, in a manner known to those skilled in the art, the objective being to enable the diamond surfaces to accept a metallic solder bond with useful adhesion. Said high-efficiency diamond material is then soldered by

10 one of its major surfaces with a 63/37 tin/lead solder to a mating copper heat sink, said soldered interface covering the entire surface of the high-efficiency diamond material, without regard to such minor defects as may be produced in the soldering attachment process. To the other side of said high-efficiency diamond material is attached by means of an appropriate gold/tin or other compatible eutectic metallic

15 solder, the back side of a silicon microprocessor presenting a surface area on the side to be affixed to the high-efficiency diamond material in excess of 1 square centimeter, but less than 6.45 square centimeters, and having been prepared as needed to accept solder bonding by means well-established in the art of semiconductor device packaging. On further integration of the (heat

20 sink/diamond/microprocessor) assembly with support devices and circuitry needed to enable operation of the microprocessor, it is found that the maximum attainable thermal transport away from the microprocessor has increased by a factor in

excess of 100% without detriment to the processor's operational or structural integrity.

Although the preferred embodiment recited above applies to the use of diamond materials in microprocessor packaging, it will be appreciated by those skilled in the art of heat transfer that the invention provides similar advantages in a wide variety of heat transfer applications. Several of these applications will be named and discussed below, without limitation of the invention thereby to those applications.

10

It is known that diamond's thermal conductivity increases rapidly as its temperature is reduced below room temperature, reaching a peak at approximately 80 degrees Kelvin. The increase in diamond's thermal conductivity at 80 degrees Kelvin compared with its value at 293 degrees Kelvin (nominal room temperature) is approximately 100 times the room temperature value. This permits diamond's advantageous use in cryogenic heat transfer applications. In cooling high performance infrared detectors, it is necessary to transport heat from the detector to a refrigeration mechanism. Thermal conductance between the detector and refrigerator is determined in great part by the materials comprising the thermal pathway. Diamond's superior cryogenic thermal conductivity enables the rapid removal of heat from cooled detectors, enhancing their performance and reducing the power required by the refrigeration system. Large-area (greater than 1 cm²

20

area) detectors can be cooled most efficiently by use of a suitable diamond thermal conduction component in the refrigeration heat transfer chain.

Heaters are employed to transfer thermal energy to materials. Many such
5 heaters employ conduction as their principal thermal transfer mechanism. A large
class of such heaters are used, for example, in heating process fluids. Frequently,
it is an important consideration to heat the target fluid as rapidly as possible,
without producing localized high temperature regions that would lead to
degradation of the target material or the heater.

10

Use of diamond as a heat spreader in contact with heating elements reduces
local thermal variations. This in turn allows more energy to be applied to the
heater without exceeding hot spot limits, resulting in faster heating operation, with
increased process throughput and improved economics. In addition, diamond's
15 very low chemical reactivity and high hardness provide excellent protection
against corrosion and wear of heater elements.

Diamond may be employed in heating applications as a coating over
heating elements or as a separate component that is interposed between a heating
20 element and its target material through means well-known to those skilled in the
art.

While embodiments and applications of this invention have been shown and described, it would be apparent to those skilled in the art that many more modifications than mentioned above are possible without departing from the inventive concepts herein. The invention, therefore, is not to be restricted except

5 in the spirit of the appended claims.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000